

# 100W, 48V POWER SUPPLY, UNV INPUT, WIRELESS DIMMING

100W, 48V Power Supply. 120-277V (UNV) input.

Casambi, Tuya, Smart Life dimming.

Wireless Bluetooth/ZigBee/Wi-Fi Dimmable LED Driver

Setting scene, area control, timing dimming, music control

Full dimming range: 0-100%

Short circuit/ Over load/ Over temperature

Flicker-free

UL & cUL, Class 2, CE, RoHS, REACH

IP66 Dry, Damp, and Wet location

9.1" x 3.1" x 1.7"

**Lighting fixtures ordered with this driver will automatically ship with 48V lighting modules.**



## Model Number Configuration

**PS-100-48-UNI-BL**

## Electrical

|                     |                |
|---------------------|----------------|
| <b>Voltage</b>      | 120-277V (UNV) |
| <b>Dimming</b>      | Casambi        |
| <b>Power</b>        | 100W           |
| <b>Lumens</b>       | N/A            |
| <b>Power factor</b> | N/A            |

## Environmental

|                     |     |
|---------------------|-----|
| <b>CRI</b>          | N/A |
| <b>Environment</b>  | N/A |
| <b>Light Source</b> | N/A |
| <b>Chip</b>         | N/A |
| <b>Life rating</b>  | N/A |
| <b>Listings</b>     | N/A |

## Mechanical

|                     |                    |
|---------------------|--------------------|
| <b>Installation</b> | N/A                |
| <b>Cord Legth</b>   | N/A                |
| <b>Dimensions</b>   | 9.1" x 3.1" x 1.7" |
| <b>Weight</b>       | N/A                |
| <b>Material</b>     | N/A                |
| <b>Finish</b>       | N/A                |

## Driver Options

|                    |     |
|--------------------|-----|
| <b>Driver code</b> | N/A |
|--------------------|-----|